



The **Black Baffle 50** is a fully adjustable 50mm downlight which has the added benefit over the *Rock 'n' Roll 35* of an integrated black baffle. This recesses the light source further into the downlight, absorbing light at wide angles to eliminate glare whilst also maintaining full light output. The inner ring can tilt to a maximum of 35° for precise beam placement.

The outer ring of this product is permanently attached to the ceiling and the two inner rings are one piece. These two inner rings are easily pulled out to reveal the lampholder. This simply pushes back in place afterwards. No clips or tools are needed, simplifying the lamp replacement process without compromising the design.

Included with this fitting is the **Slimline Emergency Conversion 12V 50W 3hr** which can be used for maintained or non-maintained operation for use with upto 50watt lamps at 6volts for 3hours. This unit is supplied with a integral 12V maintaining transformer.

Emergency packs are used in commercial buildings as a safety precaution to power outages, so that people will be able to find their way out of a building in the event of an emergency.

**Maintained Emergency Lighting:** The emergency light units are illuminated at all times using the same lamps for both normal and emergency operation. Please note maintained fittings can be wired as non-maintained.

**Non-Maintained Emergency Lighting:** A non maintained fitting is not illuminated until the event of power failure.

## DL33664B/EMERGENCY NICKEL

Nickel (Bevelled Edge) 50W  
Quicklink: Q229C

### General

Cap	GU5.3 / MR16
Colour	Nickel
Construction	Die-Cast Aluminium
IP Rating	IP20

Battery	3 hrs
Emergency Type	Maintained/Non Maintained

### Dimensions

Cut Out	80mm (Diameter)
Diameter	90mm
Horizontal Rotation	360°
Minimum Ceiling Depth	85mm
Pack Diameter	60mm
Pack Length	600mm
Vertical Rotation	35°

### Electrical

Maximum Wattage	50W
Voltage	12V