



The **Twilight Switch** can be surface mounted onto an external wall. It will switch a lamp load on during the hours of darkness. The light level at which the lamp will switch on and off is set by a lux adjuster.

Loading

- 6 amps (1500W) Incandescent or mains halogen lamps (recommended with integral safety fuse).
- 4 amps (1000W) Electronic or wire wound transformers. Fluorescent lamps (high frequency or soft start)
- 2 amps (500W) Compact fluorescent or LED lamps (about 50 lamps)
- 1 amp (250W) Most metal halide lamps and fans.

TWSW

White 1500W
Quicklink: Q29E1

General

| | |
|--------------|---------|
| Colour | White |
| Construction | Plastic |
| IP Rating | IP54 |

Dimensions

| | |
|--------|------|
| Height | 37mm |
| Length | 75mm |
| Width | 60mm |

Electrical

| | |
|-----------------|---------|
| Maximum Wattage | 1500W |
| Voltage | 240V AC |