



## PTHM3 50/65

50W Maintained / Non Maintained  
Quicklink: Q21EC

### General

Colour White

Battery Life 3 hrs

Emergency Type Maintained/Non Maintained

### Dimensions

Battery Depth 24mm

Battery Length 195mm

Battery Width 63mm

Cut Out 70mm (Diameter)

Module Depth 50mm

Module Length 200mm

Module Width 50mm

Transformer Depth 40mm

Transformer Length 100mm

Transformer Width 50mm

### Electrical

Maximum Wattage 50W

The **Emergency Conversion 12V 50W 3hr** is used for maintained or non-maintained operation for use with a maximum of 50watt lamps at 6volts for 3hours. This unit is supplied with a 'Plug In' integral 12V maintaining transformer.

Emergency packs are used in commercial buildings as a safety precaution to power outages, so that people will be able to find their way out of a building in the event of an emergency.

**Maintained Emergency Lighting:** The emergency light units are illuminated at all times using the same lamps for both normal and emergency operation. Please note maintained fittings can be wired as non-maintained.

**Non-Maintained Emergency Lighting:** A non maintained fitting is not illuminated until the event of power failure.