



## WISETRANS/REC 60

24V 60W

Quicklink: Q4A88

### General

Construction Plastic  
IP Rating IP65

Maximum Scenes Per Receiver 64  
Maximum Switches Per Receiver 16  
Radio Frequency 868.3 MHz

### Dimensions

Height 20mm  
Length 360mm  
Width 30mm

### Electrical

Input Voltage 240V AC  
Maximum Wattage 60W  
Output Voltage 24V DC  
Voltage 24V DC

The **Wise Trans/Rec 60** is a 60W 24V dimmer that is controlled by wireless switches. It can dim 24V DC LEDs. It can be programmed in 4 different ways using our wireless switches:

#### Option A - Scene Programming

Programming a 7 button switch gives you 4 scenes, master raise/lower and off. A scene is a preset level of light for each circuit in a room. For example, you can have 4 receivers in your living room. Pressing scene 1 on the 7 button switch could give the following;

Downlights = 100%

Wall lights = 80%

Pendant = Off

Low level LEDs = 55%

Pressing scenes 2,3 and 4 can give other preset levels. Any level can be programmed to each receiver.

#### Option B - Dimming Programming

Programming a 1 button switch gives you on/off with a quick press and dimming up and down while holding the switch. When turning the lights on you can choose to always bring on the lights at 100% or the last dimmed level.

#### Option C - Switching ON only

Programming a 1 button switch gives you only ON. This function is used to program multiple circuits to ON.

#### Option D - Switching OFF only

Programming a 1 button switch gives you only OFF. This function is used to program multiple circuits to OFF.

A receiver is not limited to one of the programming options. E.g. you can program a switch for scene control, another switch for dimming and another switch for master ON/OFF.

#### Wireless Switches and Remotes

A 7 button switch must be used if you require scene setting, Option A. Any button switch can be used when programming options B,C and D. To view other switches click the links on the right of this page, for example Wireless ID switches.

## Wise Controls Introduction Video

