



The **Feelux Booster** is used in conjunction with our *Seamless DimLine/DimSlim* range of products. Currently, if using a Feelux wired dimming switch or interface, a maximum of 10 fluorescent fittings can be used per channel. Use this product at the tenth fitting from the dimming switch or interface and the connecting capability extends 20 more pieces.

Each booster can run 2 channels, with 10 fluorescent fittings on each and up to 400W per dimmer regardless of channel. A separate power feed is required. Multiple boosters can be used.

Specification

- 2 channel
- Maximum connection: 10 pieces of Seamless DimLine/DimSlim per channel and up to 400W per dimmer regardless of channel
- Input power: AC 90-240V
- Frequency: 50/60Hz
- Output protocol: PWM 400Hz

DIMSLIM EA02

White 400W
Quicklink: Q1C34

General

Colour	White
Construction	Plastic
IP Rating	IP00

Maximum No. Units Inline 20

Dimensions

Depth	45mm
Length	115mm
Width	23mm

Electrical

Maximum Wattage	400W
Voltage	240V