

Rania (Dimming)

Rania Master 2 Gang Dimmer
Chrome 2x250W



MR. RESISTOR[®]
Lighting Specialist Est. 1968



RNDU-252BFBCM CH

Chrome 2x250W
Quicklink: Q1805

General

Colour	Chrome
Construction	Plastic
IP Rating	IP00

Dimensions

Depth	25mm
Length	85mm
Width	85mm

Electrical

Maximum Wattage	500W (2 x 250W)
Voltage	240V

One **Rania Master 2 Gang Dimmer** can control up to ten locations using accessory slave dimmers. Each unit intelligently communicates to another to ensure that the light level chosen is memorised and stays constant on all dimmers.

This ultraquiet intelligent dimmer can softly fade lights on or off. Select your desired light level using the arrow buttons. Each press up or down is indicated by the green LED's. One tap on the on/off button brings the light last level on. A double tap softly fades up to full brightness the circuit on or off.

Important Notes

- Only use electronic transformers when using this switch to dim low voltage fittings such as downlighters
- To avoid overheating and possible damage to other equipment, do not use this product to control fluorescent lighting fixtures, motor-operated or transformer supplied appliances
- Only one dimmer can be used in a 2 way circuit
- The dimmer requires a minimum lamp wattage of 40W. Do not exceed the maximum rating of 500W
- This fitting may not work with LED lamps
- Suitable for low and mains voltage load types