



The **Wise Converter 3** is a power supply that is used to drive 350mA LEDs, but only requires an input of anything between 6 to 30V. This makes it ideal for use on boats, cars, caravans, or motorbikes where the supply is limited to low voltage, or for powering direct from a battery.

Any wattage 350mA LED can be used, but cannot exceed a maximum of 8 units wired in series, or 7W.

This product is rated IP68 so is suitable for use in wet and humid environments. Includes thermic and short circuit protection.

## WISE CONVERTER 3

6-30V 350mA  
Quicklink: Q187D

### General

Colour	Black
Construction	Plastic
Dimmable	No

### Dimensions

Height	22mm
Length	21mm
Width	41mm

### Electrical

Amperage	350mA
Maximum Wattage	7W
Voltage	6-30V