Switching On/Off

Wise Box 2 Channel Kit includes Keyfob & Keypad

2 Channel 2 x 1000W



WISEBOX 2CH KIT

2 Channel 2 x 1000W
Quicklink: Q2E9D

General	
IP Rating	IP54
Detection Range	200m
Dimensions	
Depth	80mm
Height	184mm
Width	200mm
Electrical	
Amperage	20A
Maximum Amps / Circuit	10A
Minimum Wattage per Circuit	1W
Voltage	240V

The **Wise Time Lag Box Kit** is a receiver that has three functions. The functions are on/off switching, push-to-make switching and timelag switching. The timelag function can be set to work between 1 second and 9 hours. This is very popular when installing lighting for communal hall ways and stair cases. As the switches are all wireless they can be placed anywhere with minimal effort.

The receiver has two 10 amp channels with a 200 metre range. Thee channels can be changed from switching to push-to-make.

It can be programmed in 4 different ways:

Option A - Push-to-make
The circuit will work as push-to-make from a single button.

Option B - Single Button Switching ON/OFF
The circuit can be turned ON/OFF from a single button.

Option C - Two Button Switching ON/OFF
The circuit can be turned ON/OFF from two buttons, for independent ON and OFF.

Option D - Time Delay
The circuit can have a timer on it. Use a single button to turn the lights on. The timer will turn the circuit off after the set time has passed. Use a two button switch for control. To turn on, press button 1 and either wait for the dela time or press button 2 to turn off.

Wise Controls Introduction Video

