

## Surface Mounted Sensors

IR LED Dual Function Cabinet - Movement Sensor  
Black 12V=15W, 24V=30W



**MR. RESISTOR**<sup>®</sup>  
Lighting Specialist Est. 1968



### **IRDS-BK-LED-JB4**

Black 12V=15W, 24V=30W  
Quicklink: Q5593

A IR LED dual function cabinet and movement sensor, can be used either as a sensor to switch on and off lights when opening and closing cabinet doors or as an external mounted sensor operated by moving your hand over the sensor to activate the lights.

#### **General**

Colour	Black
Construction	Plastic
IP Rating	IP20

#### **Dimensions**

Length	14mm
Width	12mm

#### **Electrical**

Voltage	12V, 24V
---------	----------