Chameleon Colour Change RGB

Wise Prism Master

12/24V 5 x 100W





WISERGB/W/W

12/24V 5 x 100W

Quicklink: Q5529

General

Construction	Plastic
IP Rating	IP54
Radio Frequency	868.3 MHz
Range for Metal Switch	50m Max Line Of Sight
Range for Plastic Switch	100m Max Line Of Sight

Dimensions

Height	51mm
Length	230mm
Width	70mm

Electrical

Input Voltage	12-24V
Maximum Wattage	500W (5 x 100W)
Minimum Wattage	1W
Voltage	24V

The **Wise Prism Master** is a RGBWW or WWWWW dimmer with built-in radio receiver for the control of RGB (red, green, blue) and tunable white controller for 12/24 Vdc LED. It allows adjusting the temperature of the colour, mixing the outputs from cool white to warm white. Ideal for outdoor installations using box IP54. Maximum wattage is 100W for each channel, which is 5 x 100W.

- **If controlled with 7-channel wireless transmitter, you can choose from 8 pre-set colours (changeable at any time) or activate the automatic colour cycle**
- **The RGB and white outputs are controlled independently by transmitter or manually operated pushbuttons**
- **It is possible to adjust the intensity of the pre-set colours and to save the new value (Light memory)**
- **Function of gradual light switching on and off (Fade)**
- **Possibility to memorize up to 42 transmitters**

WISERGBWW Programming

